



CPS 2

Cable power splitter/combiners for coupling 2 antennas to a common feeder

- The CPS 2 series of power splitters are manufactured using high quality coaxial cable and connectors.
- The CPS 2 power splitters use quarter wave coaxial cable transformer sections to match two or more loads to one source.

DESCRIPTION

- Phase shift can be incorporated to produce electrical beam tilt with phased dipole arrays.
- The junction points on the CPS 2 power splitters are completely encapsulated with epoxy resin within a high grade aluminium tube totally preventing dust and moisture ingress.

ORDERING DESIGNATIONS

TYPE	FREQ.	PRODUCT NO.
CPS 2-78	66 - 88 MHz	123001050
CPS 2-98	88 - 108 MHz	123001051
CPS 2-127	110 - 140 MHz	123001052
CPS 2-160	140 - 180 MHz	123001053
CPS 2-200	180 - 220 MHz	123001054
CPS 2-405	380 - 430 MHz	123001055
CPS 2-445	420 - 470 MHz	123001056

SPECIFICATIONS

ELECTRICAL	
FREQUENCY RANGE	66 - 470 MHz
INPUT IMPEDANCE	50 Ω
BANDWIDTH	± 20% of centre frequency
VSWR	<1.3:1
MAX. INPUT POWER	500 W
MECHANICAL	
INPUT CONNECTION	1 m length RG 213 c/w 'N' type female
OUTPUT CONNECTION	'N' type male on quarter-wave length RG 11 cable





CPS 2

Cable power splitter/combiners for coupling 2 antennas to a common feeder

BODY	Aluminium tube 38.1 mm
INSULATOR	Epoxy resin encapsulant

